

DMM-113C Pocket Digital multimeter

DMM-113C is a portable, compact, lightweight 3 3/4 Digit Auto range pocket digital multimeter, fully functional, stable performance, high accuracy, low power consumption, the new structure, safe, reliable, easy to operate, Easy to use, durable for the majority of users.

This is the ideal measurement instrument and can be used in homes, schools, telecommunications, manufacturing, petroleum, power, chemical and other fields, circuit / electrical equipment maintenance and repair.



1. Auto power off
2. Auto range
3. 4000 display count
4. Data hold and relative mode
5. Capacitance measurement
6. AC/DC current measurement

Function	Range	Accuracy
DC voltage	4V/40V/400V/600V	±(0.8%+3)
AC voltage	4V/40V/400V/600V	±(1.2%+3)
DC current	400μA/4mA/40mA/400mA	±(1.0%+3)
AC current	400μA/4mA/40mA/400mA	±(1.5%+3)
Resistance	400Ω/4KΩ/40KΩ/400KΩ/ 4MΩ/40MΩ	±(1%+2)
Capacitance	4n/40n/400n/4μ/40μ/100μF	±(4%+3)
Frequency	99.99Hz ~ 99.99KHz	±(0.5%+3)
Display count		3999
Auto range		V
Duty cycle	0.1%~99.9%	V
Diode		V
Auto power off	Around 30 minutes	V
Continuity buzzer		V
Low battery indication	≤2.4V	V
Data hold		V
Relative mode		V
Input impedance for DCV	Around 10MΩ	V
Power	3V battery (CR2032)	
Weight	76g	
Size	110mm x 58.2mm x 10.8mm	